

PIR DETECTOR VIA RADIO



- VESTA radio PIR detector
- 15 meter coverage, 130 °
- 45 kg anti-pet (configurable remotely)
- Automatic PIR sensor calibration
- Double detection function configurable from App Installer
- 2 levels of sensitivity (remotely configurable)
- Efficient dwell time between detections
- Optional swivel bracket
- It works with 1 CR123 battery
- 5.8 year battery life
- Grade 2 certificate



Reference / Model

VESTA-177 / IR-35SL-F1

specs

Detection range: 15 meters, 130 °
 Automatic PIR sensor calibration
 It has a double detection function (the alarm is confirmed in case of two detections in a short time), configurable from the Installer App
 Efficient standby time between detections
 RF frequency: 868MHz
 Microprocessor controlled with advanced ADSP algorithms for false alarm immunity
 Anti-pets up to 45 kg
 Two selectable sensitivity levels
 Remote configurable sensor sensitivity and anti-pet function
 High immunity to false alarms
 Tamper Protection
 Superior white light and noise rejection
 Automatic energy saving mechanism
 Random supervisory signals for system integrity
 Rejection of radio interference
 Sensitivity control with temperature compensation
 Works with 1 CR123 battery
 5.8 year battery life
 -10 ° C ~ + 45 ° C operating temperature
 Relative humidity up to 85% (non-condensing)
 2.3 ~ 2.5 meter installation height
 Optional swivel bracket
 Grade 2 Certificate