

VESTA radio extender / repeater

✓ GRADE 2

- VESTA radio extender / repeater
- Extends the communication range between the sensors and the Control panel
- Rechargeable backup battery
- Tamper proof
- Includes 220V power supply
- Grade 2



Reference / Model	VESTA-030 / RP-29-F1
Features	
Extends the radio signal of any PIRCAM	
Extends communication range between alarm gateway and sensors	
Repeaters can repeat each other	
Intelligent signal filtering eliminates repetitive signal transmissions	
Includes Battery Backup: Rechargeable AAA Ni-Mh battery pack, 750 mAh	
Tamper protection	
Compatible with VST-862-F1 series detectors	
Four LEDs show power, installation, transmit, and receive status	
Periodic supervisory signals to verify system integrity	
Suitable for residential and commercial use	
EN50131 Grade 2 certified	

VESTA radio extender / repeater

Reference / Model	VESTA-030 / RP-29-F1
Specifications	
RF frequency: 868MHz	
Power: 12V, 1A	
Battery back-up included: Rechargeable AAA Ni-Mh battery pack, 750 mAh	
Battery life of up to 15 hours	
-10 ° C ~ + 45 ° C operating temperature	
Relative humidity up to 85% (without condensation)	
Dimensions: 186 x 130 x 30mm	
Grade 2	