

VESTA 4-KEY BIDIRECTIONAL PUSH BUTTON

✓ GRADE 2

- VESTA 4-button bidirectional radio button
- Armed / disarmed, start and panic
- Cover to prevent inadvertent use
- Suitable for security and home automation
- It works with 1 CR2032 3V lithium battery
- 8 year battery life
- UL1023
- EN50131 Grade 2, ClassII



Reference / Model

VESTA-144 / RC-16-F1-2W

Features

Two-way communication
Allows control of the security system
Four buttons: Arm / Disarm / Start / Panic
Front sliding cover prevents inadvertent use
Durable and scratch resistant buttons
Lightweight keychain design
Low battery detection
Suitable for home automation and security installations
Meets UL1023
Certified EN50131 Grade 2, ClassII

Specs

RF frequency: 868MHz
Power supply: 1 3V CR2032 lithium battery
8 year battery life
-10 ° C ~ + 45 ° C operating temperature
Relative humidity up to 85% (non-condensing)
Dimensions: 50 x 30 x 15 mm